

**\*\*\*READ & SAVE THESE INSTRUCTIONS \*\*\***  
**ACCESS LIGHTING**  
**MODEL 53301**  
**INSTALLATION & OPERATION INSTRUCTIONS**

1) TOOLS AND MATERIALS REQUIRED

- ❖ Blade Screwdriver
- ❖ Star Screwdriver
- ❖ Wire Cutters
- ❖ Wiring supplies as required by Electrical Code
- ❖ Step Ladder

**Attention:**

**Before assembling your lighting fixture, please read the following instructions. If you feel you do not have sufficient electrical experience, refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.**

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon outlet box. The box must be directly supported by the building structure and U.L. Recognized.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

**NOTE:**

**The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. The person(s) caring for and operating the fixture must supply these factors.**

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

1. Mounting Hardware Package
2. 1,2,3 or 4 Glass Shades (Model Dependant)
3. 1,2,3 or 4 Bulb Protectors (Model Dependant)
4. Fixture Assembly
5. 1,2,3 or 4 x 40W HGN/120V JCD (G-9 Base)

(4) PREPARE THE FIXTURE

1. If you are replacing an existing fixture, disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Lay the un-assembled fixture on a soft surface and carefully remove all the packing material.
3. Mount the **Fixture Back Plate** to the **Junction Box** by inserting the supplied **Screws** into the screw holes located on the circumference of the **Back Plate** hole.
4. Attach the supply wire to the fixture wires in the following manner: The **Black supply wire** attaches to the **Black fixture wire** and the **White supply wire** attaches to the **White fixture wire**.
5. Attach the **Green/Ground wire** from the fixture to the **Electrical Supply Wire** or to the **Green Screw** located on the **Universal Crossbar**.
6. Secure these connections with supplied **Wire Connectors** and tape these connections with **U.L Listed electrical tape**. Tuck all of the wires into the **Junction Box**.
7. Locate the **Screw Holes** on either end of the **Fixture Back Plate**. Use these holes to provide the fixture with added support and secure the location of the fixture.
8. Place the **Front Fixture Plate** over the **Back Plate** ensuring that the holes at the top and bottom of both plates align. Insert the screws and tighten securely.
9. Insert the **G-9 Bulbs** and place the **Tempered Bulb Covers** over the Bulbs. **DO NOT EXCEED WATTAGE AS INDICATED ON WARNING LABEL.**
10. Place the **Glass Shade** onto the **Metal Frame** and secure with the **Glass Retaining Rings**.
11. Restore electricity and enjoy your new lighting fixture.

**CAUTION:**

- **Ensure that the Fitting is Cool and Switched off, Before Changing Bulbs.**
- **Do Not use Bulbs Exceeding Maximum Wattage , As Per Caution Label.**
- **Do Not Use Lamps without the Supplied Tempered Protection Glass**
- **Do Not Touch the Bulbs or Protective Glass while fixture is in operation.**
- **Do not operate fixture next to combustible material.**

