

access

LIGHTING

Read & Save these Instructions Models: 23950/23951/23952 Installations & Operation Instructions

(1) TOOLS AND MATERIALS REQUIRED

- ❖ BLADE SCREW DRIVER
- ❖ WIRE CUTTERS
- ❖ WIRING SUPPLIES AS REQUIRED BY ELECTRICAL CODE
- ❖ 1Lt x 60W/A-19/Medium Base Lamp (23950)
- ❖ 1Lt x 100W/A-19/Medium Base Lamp (23951/23952)

Attention:

Before assembling your lighting fixture, please read the following instructions. If you feel you do not have sufficient electrical experience, refer to a do-it-yourself wiring handbook or have your fixture installed by a qualified licensed electrician.

(2) GENERAL

1. To ensure the success of the installation, be sure to read these instructions and review the diagrams thoroughly before beginning.
2. All electrical connections must be in accordance with local codes, ordinances, or the National Electrical Code. If you are unfamiliar with methods of installing electrical wiring, secure the services of a qualified licensed electrician.
3. These fixtures are intended for mounting to a standard 4" x 2 1/4" deep metal octagon outlet box. The box must be directly supported by the building structure and U.L. Recognized.
4. Before commencing with the installation, **disconnect the power by turning off the circuit breaker** or by removing the fuse at the fuse box. Turning the power off using the light switch is not sufficient to prevent electrical shock.

NOTE:

The important safeguards and instructions appearing in this manual are not meant to cover all possible conditions and situations that may occur. It must be understood that common sense, caution and care, are factors that cannot be built into any product. These factors must be supplied by the person(s) caring for and operating the fixture.

(3) UNPACKING THE FIXTURE

On checking the contents of the box you will find;

- ❖ 1 x Glass Diffuser
- ❖ Mounting Hardware
- ❖ Fixture Assembly
- ❖ 6"-16"-22" Rods
- ❖ Mounting Plate

(4) PREPARE THE FIXTURE

Refer to attached illustration of fixture parts and assembly.

1. If you are replacing an existing fixture disconnect and remove the old fixture. Expose the supply wiring from the outlet box.
2. Lay the un-assembled fixture on a soft surface and carefully remove all the packaging material.
3. Attach the supplied Mounting plate to the outlet box with the supplied Mounting screws (1).
4. Your fixture includes a 6", 16" and 22" rod (additional rods are available for purchase-the maximum drop is 10'). Choose the appropriate rods to meet the desired length of your fixture. Place the longest rod (2) at the bottom and the shortest rod (8) at the top.
5. Slide the longest rod (2) through the top washer and cap (6), the glass shade (5) and the bottom washer (4).
6. Position the socket assembly (3) close to the bottom rod (2), feed the fixture wire through the bottom rod (2) and any additional rods. Screw the socket assembly (3) into the bottom rod (2).
7. Screw all the rods together.
8. Place the swivel (10) and shortest rod (8) which should be attached, into the canopy (11), such that the bottom of the short rod (8) is positioned to screw into the rod below. Feed the wire into the short rod (8) and swivel (10) and then screw the top rod (8) into the rod below.
9. Feed the supply wires through the outlet box and attach the supply wires to the fixture wires. Connect the **BLACK supply wire** to the **Black wire** of the fixture with supplied **Wire Nuts (9)** ensuring a secure connection.
10. Connect the **WHITE supply wire** to the **White wire** from the fixture a secure with supplied **Wire Nuts**.
11. Attach the **ground (GREEN) wire** from the fixture to the **outlet box ground terminal** (or to the box ground wire).
12. Secure all wire nuts connections with UL listed electrical tape. Tuck wires carefully into Junction box.
13. Position the **canopy (11)** over the **Mounting plate** such that the holes on the sides of the canopy line up with the holes on the **Mounting plate**. Secure the canopy to the **Mounting plate** with the supplied **screws (12)**.
14. Insert **bulb(13)** into socket. **DO NOT EXCEED WATTAGE AS PER CAUTION LABEL.**
15. Restore electricity and check the operation of your new lighting fixture.

CAUTION:

- **Ensure that the Fitting is Cool and Switched off, Before Changing the Bulb.**
- **Do Not use Bulbs Exceeding Maximum Wattage, As Per Caution Label.**
- **Do Not place lamp near combustible material**

MODELS 23950/23951/23952

